

Setting up a Printer

This activity steps through changing Lightwriter setups for a Printer.
This activity takes about 30 secs.



- a) Press **On/C**
- b) Press **Mem** then **↶** to enter the setup menu.
- c) Press the **P** key repeatedly to find **Port 1** setup (or **Port 2**, if **Port 1** is already being used)
- d) Change setting to **Printer** using **+ -** key
- e) Press the **P** key once more to find **Printer** setup.
- f) Change setting to **MiniPrinter** using **+ -** key
- g) Press **Off**
- h) Plug the **Printer** into **Port 1** (right hand side of Lightwriter) (or **Port 2**, left hand side of Lightwriter)

To print:

Keyboard Lightwriter

- i) Press **On/C**
- j) Type some text
- k) Press **Mem** then **6** to print

Scanning Lightwriter

- i) Press Scan switch to turn on Lightwriter
- j) Enter some text
- k) Select **⇒** then **⇒** then **Print** to print